



RG 227

NOISE GENERATOR

Specifications:

Frequency range	1 - 2,150 MHz
Output level	min. 73 dB μ V at 1 MHz bandwidth
Frequency response	\pm 1 dB to 1 GHz \pm 2 dB from 1 GHz to 2,15 GHz
HF splitter	0 or 10 dB
Battery charge	via external power supply unit AC 170 - 240 V
Power supply	integrated battery pack
Weight	0.2 kg with batteries
Dimensions	H: 103 mm, W: 55 mm, L: 24 mm
Scope of delivery	measuring cable, AC/DC power supply unit, manual, transport case

Like the RG226, the RG227 allows you to control frequency progressions of entire reception and distribution systems as well as those of individual components.

The RG227 does not have as many functions as the RG226, however it does offer the same complete frequency range from 1 MHz to 2,150 MHz.

The output level can be reduced by 10 dB.